



SmartBank *PRO*

Advanced Split Charge System

User & Installation Guide

Version 1.3

**Merlin Equipment Ltd
Unit 4, Cabot Business Village
Poole
Dorset BH17 7BA
United Kingdom
T: +44 (0) 1202 697979**

**Merlin Power Systems
332-4 West Montauk Highway
Hampton Bays
New York
NY11946
United States of America
T: +1 (631) 594 5102**

www.merlinequipment.com



WARNING

Your attention is drawn to “Caution!” and “Warning!” statements throughout this manual.

“Caution!” refers to practices that may cause damage to the SmartBank PRO or your electrical system.

“Warning!” identifies practices that may cause injury or death.

SmartBank PRO is designed for installation by qualified and competent electrical engineers.

Qualified and competent engineers will be familiar with safe working practices, local health & safety legislation and the proper and safe use of tools and equipment. Therefore not all obvious practices that may lead to system damage, injury or death are detailed within this manual. If you are in anyway unsure about any aspect of the installation or use of SmartBank PRO, contact your Dealer or Merlin Power Systems for advice.

Precautions

- This product is designed for use in 12Volt DC and 24Volt DC vehicular systems depending on model. Use in other than its designed application may result in fire, electric shock or other injury.
- DO NOT disassemble, modify or alter. Doing so may result in an accident, fire or electric shock.
- USE ONLY in vehicles with a NEGATIVE GROUND. Failure to do so may result in fire, electric shock, damage or other injury.
- FUSES: Use the correct ampere rating when replacing fuses. Failure to do so may result in fire, injury, electric shock or damage.
- DO NOT install or operate the CPU in an explosive atmosphere.
- DO NOT install or expose the CPU to excessive temperatures or humidity.
- If in any doubt consult a suitably qualified and competent engineer or the supplier.
- DO NOT substitute Contactors or switches with any other types that have not been approved and tested.
- MAINTENANCE. If you have problems or suspect device failures DO NOT attempt to repair the unit yourself. Return it to your Dealer or Merlin for servicing.


Certificate of Conformity



Declaration of Conformity

Merlin Equipment Limited, Trading As Merlin Power Systems hereby declares that the product marketed as SmartBank PRO is in compliance with the requirements of EU Electromagnetic Compatibility (EMC) Directive 89/336/EEC.

VCA Approval Number: 10R-058879



Test report: TRA-025367-38-00A



SmartBank PRO complies with RoHS (Reduction of Hazardous Substances) Directive 2002/95/EC.. SmartBank PRO contains no Lead. At the end of life, SmartBank PRO should be disposed of as normal electrical waste.

SmartBank PRO has been tested to and surpasses ISO-7637-2 for use on vehicles.

Signed:

A handwritten signature in blue ink, appearing to read 'James Hortop'.

James Hortop
Managing Director
Merlin Power Systems UK

Introduction

Thank you for purchasing a Merlin SmartBank PRO.

SmartBank PRO is a highly advanced split charging system designed to allow charging of multiple battery banks.

SmartBank PRO may be used for split charging of two or three independent battery banks. It is supplied with either a single split charge contactor (for two battery banks) or two contactors (for three battery banks).

Please take the time to read and understand this manual before installation and use.

Contents.

Page	Description
2	Warnings
3	Precautions
4	Approvals and Conformity
6	Package Contents
7 – 9	Installation
10	Wiring Schematic
11	Set-up and Adjustments
12	Emergency Parallel Switch and Notes
13	After Installation
14	Warranty and Servicing Details

Package Contents:

Two Battery Bank Version (1 Auxiliary bank):

Models: 04-8011(12V) and 04-8013(24V)

- **SmartBank PRO CPU x1**
- **SmartBank PRO Contactor x1.** *Part Number: SU80-5162PL (12V) or Part Number: SU80-5163PL (24V)*
- **Emergency Parallel Switch x1**
- **Fuse Kit & rubber blanking plugs**
- **User Installation Guide (this document)**

Three Battery Bank Version (2 Auxiliary banks):

Models: 04-8012(12V) and 04-8014(24V)

- **SmartBank PRO CPU x1**
- **SmartBank PRO Contactor x2** - *Part Numbers: SU80-5162PL (12V) or Part Number: SU80-5163PL (24V)*
- **Emergency Parallel Switch x1**
- **Fuse Kit & rubber blanking plugs**
- **User Installation Guide (this document)**



SmartBank PRO CPU



Contactor



Emergency Parallel
Switch

INSTALLATION

- **Warning!** Isolate power supply before starting installation.

Positioning of Parts

The following should be observed as parts of SmartBank PRO are designed for wet/dirty environments but others are not.

Main CPU.

Caution! Damage will occur if the CPU is allowed to get wet.

Warning! Do not install the CPU in a petrol/gas engine room environment.

The CPU is designed for location in a dry environment (such as on cab side of engine room bulkhead or a cupboard). It is suitable for installation in drier engine compartments on boats. However, it is not sealed against moisture ingress. The CPU is **NOT** suitable for installation or operation in atmospheres where there is a risk of ignition or explosion.

Contactors

These are designed to be installed under hood, in wet engine room environments and battery compartments. The contactors are IP66 rated and will withstand hose downs.


Emergency Parallel Switch

The switch is IP66 rated and fully waterproof. It can safely be installed in engine rooms, on dashboards, on flybridges etc. Will withstand hose downs.


Wiring Diagram

Wiring Diagram covers the majority of installations.

Typical 2 Battery Layout:




Typical 3 Battery Layout:



Prioritising Charging:

In the case of a three battery bank system, it is possible to prioritise charging. In the example above (3 battery system), the engine battery would charge first, then the auxiliary and then the 2nd auxiliary battery. This priority can be changed by moving the contactor connections. This allows you to execute a priority charge strategy depending on the order in which you want batteries charged and from which charge sources.




Caution & Warning: We recommend that appropriately rated fuses or circuit breakers are inserted between batteries and contactors to protect against short circuits. These should be located as close as possible to the battery positive terminal of each battery bank. SmartBank PRO is supplied also with small inline fuses for the B1 and B2 sense wires – these must be used in every installation.



Contactor Mounting and Rating:

The Contactors supplied are IP66 rated and Ignition Protected. They may be used in external areas (such as under the hood). Contactors are rated for charging systems of up to 200A continuously. They will also handle intermittent cranking current of engines of up to 725A.

The contactor should be mounted vertically (contact studs pointing upwards) or horizontally. The performance of the contactor may be impaired if mounted upside down.



CPU Wiring:




Caution: Ensure always that the correct polarity is observed on the contactor coil control wiring. Serious damage to the SmartBank CPU will occur if these wires are shorted or connected the wrong way round.


Set Up and Adjustments

SmartBank PRO will work 'out of the box' for both 2 and 3 battery bank systems.

Installation Example: 2 Battery System



Installation Example: 3 Battery System



Manual adjustment of split charge settings is achieved using rotary trimming potentiometers ("trim pots") which are accessible through the front case of the CPU.


The trim pots on the front of the CPU allow you to adjust the Connect Voltage, Disconnect Voltage and Hold Timer settings.

Connect range = 13.0 to 13.8 Vdc (26.0 to 27.6V for 24V Operation)

Disconnect range = 12.5 to 13.3 Vdc (25.0 to 26.6V for 24V Operation)

Hold timer range = 0 to 255 seconds.

Adjustment is made by rotating the trim pots using a trimming tool or a small (1.5mm) flat-blade screwdriver. These are accessed through holes in the front face of the enclosure. Protective rubber blanking plugs cover the holes and need to be removed in order to adjust the trim pots.



The left hand preset adjusts the connection voltage threshold. The middle preset adjusts the disconnection voltage threshold. Voltage adjustment range is almost perfectly linear.

For example, with the control in the 12 o'clock position, this would be in the middle of the adjustment range (e.g. 13.4 Vdc for Connection).

The right hand control adjusts the time delay between zero and 255 seconds and again the adjustment is linear.

For a 3 battery bank system, the 2nd contactor will operate at the same Connect Voltage, Disconnect Voltage and Hold Timer settings as the first. However, a small time delay is built in which activates/deactivates the 2nd contactor after the 1st.

Emergency Parallel Switch

The emergency parallel switch, when pressed, will close the contactor(s) and hold all batteries in parallel for the same time period as the Hold Timer is set for. This allows for emergency jump starting of the engine if the engine battery has been allowed to run flat or fails.

The LED on the emergency parallel switch will be illuminated whenever the split charge contactor is connected

Notes.

Digital Signal Processing

SmartBank PRO senses and processes voltages using a Digital Signal Processor (DSP) which filters out transient spikes and electrical noise preventing SmartBank PRO connecting/disconnecting erroneously.

The DSP operation means that SmartBank PRO will take time to respond to sudden changes in voltage so it may appear that there is a short time-lag between the voltage reaching a certain level and the SmartBank PRO reacting to it. This is normal operation.

Bi-Directional Charging

SmartBank PRO acts as a Bi-Directional charge system. This means that it will sense charge on both batteries installed. Therefore, it will operate when say, the engine is running (and charging the engine battery) and, when say, a battery charger is running (and charging just the auxiliary battery). SmartBank PRO will handle any number of charge sources no matter which battery they are connected to.

Note that SmartBank PRO has two voltage sensors and is bi-directional for Battery Banks 1 and 2. In systems using 3 battery-banks, it is mono-directional for battery 3. Therefore, if you wish for charge sources to charge all batteries, they should be connected to battery banks 1 or 2. Connecting a charge source to battery bank 3 will mean that only battery 3 is charged from that specific charge source.

After Installation:

After installation and set-up, the rubber blanking plugs (provided) should be re-placed into the holes in the front of the unit. Note that they are designed to be difficult to remove so make sure you are finished before inserting them! The rubber blanking plugs restrict ingress of moisture and dirt into the CPU.

IF you are unsure about any aspect please consult a suitably qualified engineer, your Dealer or Merlin Equipment Ltd before commissioning the unit.

Product Specifications

12V Models			24V Models	
Part #	04-8011	04-8012	04-8013	04-8014
Number Of Batteries	2	3	2	3
Contactor Current Continuous	200A			
Contactor Current 5 mins	250A			
Contactor Current Cranking	725A			
Power Consumption	<10mA		<6mA	
CPU Dimensions LxWxH (inch)	68x110x32mm (2.67x4.33x1.26)			
CPU Weight ex cables (lbs)	178g (0.39 lbs)			
Contactor Dimensions LxWxH (inch)	91x50x39mm (3.59x1.97x1.54)			
Contactor Weight (lbs)	375g (0.83 lbs)			

Warranty

SmartBank PRO is warranted to be free of defects caused during manufacture for a period of 2 years from purchase. The warranty may be invalidated if the device has been altered, misused, installed incorrectly or operated in adverse conditions described in the “Precautions” section of this document.

What does this warranty cover and how long does it last? This Limited Warranty is provided by Merlin Equipment Limited. (“Merlin”) and covers defects in workmanship and materials in your SmartBank PRO. This warranty period lasts for 24 months from the date of purchase at the point of sale to you, the original end user customer, unless otherwise agreed in writing (the “Warranty Period”). You will be required to demonstrate proof of purchase to make warranty claims.

This Limited Warranty is transferable to subsequent owners but only for the unexpired portion of the Warranty Period. Subsequent owners also require original proof of purchase as described in “What proof of purchase is required?”

What will Merlin do? During the Warranty Period Merlin will, at its option, repair the product (if economically feasible) or replace the defective product free of charge, provided that you notify Merlin of the product defect within the Warranty Period, and provided that Merlin through inspection establishes the existence of such a defect and that it is covered by this Limited Warranty.

Merlin will, at its option, use new and/or reconditioned parts in performing warranty repair and building replacement products. Merlin reserves the right to use parts or products of original or improved design in the repair or replacement. If Merlin repairs or replaces a product, its warranty continues for the remaining portion of the original Warranty.

Period or 90 days from the date of the return shipment to the customer, whichever is greater. All replaced products and all parts removed from repaired products become the property of Merlin.

Merlin covers both parts and labour necessary to repair the product, and return shipment to the customer via a Merlin-selected non-expedited surface freight within the contiguous United States and Canada. Alaska, Hawaii and outside of the United States and Canada are excluded. In Europe, this is the EMEA. Contact Merlin Customer Service for details on freight policy for return shipments from excluded areas.

How do you get service? If your product requires troubleshooting or warranty service, contact your merchant. If you are unable to contact your merchant, or the merchant is unable to provide service, contact Merlin directly at: Merlin Equipment Ltd, Unit 4, Cabot Business Village, Poole BH17 7BA, United Kingdom. Tel: +44 (0) 1202 697979.