

30S12E / 30S24E



Pure Sine Wave Inverter 30S12E / 30S24E 300W 12VDC/24VDC



Key Specifications/Special Features:

| | | |
|--|----------------------------------|---|
| Pure Sine Wave Inverter 30S12E/30S24E 300W 12VDC/24VDC | Item number: | 30S12E / 30S24E |
| | Rated input voltage: | 12VDC / 24VDC |
| | Output power: | Continuous: 300W 15 Minutes: 350W Surge: 500W |
| | Output voltage: | 230V AC +/- 5% |
| | Output frequency: | 50Hz |
| | Output wave form: | Pure sine wave |
| | Total harmonic distortion: | < 3% |
| | No load current draw: | 230V AC: < 0.5A ; < 0.4A |
| | Input voltage range: | 10.5V to 15V / 21V to 30V |
| | Low voltage alarm: | 10.5V / 21V |
| | Low voltage shutdown: | 10V / 20V |
| | Efficiency up to: | 85% |
| | Dimensions (mm): | 210 x 147 x 66mm |
| | Weight: | 1.4kg |
| | Safety/Quality approval details: | CE/E-mark |

Applications:

- Home electronics, office equipment, small tools and appliances
- Battery chargers for camcorders, laptop computers, cellular phones and power tools
- Ideal for camping, boating, caravans, mobile office, field work, emergency power and many other uses
- Oxygen concentrators